

Dreamax

Tuning Instructions

1. Press Menu
2. Press down arrow key Go to INSTALLATION
3. Go to Manual Scan
4. Enter pin 0000
5. SAT NAME should be OPTUS-B3 (If not then press OK & select Optus B3 from the list.)
6. Highlight TP Frequency Press right arrow key and look for the number 12545 .
If not then Press the Green button (SOUND) . It will ask for Add, Modify, Delete. Press OK on Add.
Press the numbers 12545 from your remote . Press down arrow key highlight Polarisation change to “Vertical”
and press the down arrow key Highlight Symbol rate and press the numbers 22500 from the remote.
7. Polarisation should be Vertical (if it is horizontal, press right arrow key and make it vertical)
8. Symbol Rate should be 22500
9. Scan Mode should be All
10. Network Search should be ON (if it is off, press right arrow key and make it on)
11. Check Level and Quality should be GREEN in Colour
12. Press Red button on remote control (LANG) for scanning the channels.
13. If message appears as “Same TP Exists” then press Exist
14. “Please wait to save data” will appear. Press OK
15. Press Exit button thrice to go out of all the menus and press OK to get list of channels
& look for the Zoom